

# JTECH<sup>®</sup> EXTEND Two-Way Radios

## Wireless Cloning

Wireless cloning allows you to easily copy radio settings from one radio (the master) to all other radios within range without the use of wires or cables.



### Master Unit

You will first need to determine which of your radios is going to be your master unit. This will be the one radio to which all of your other radios will match up to.



### Turn On Cloning

Begin with the radio in the off position. Hold down the Push-To-Talk button and the S/M key at the same time while turning the radio on.



### If Done Correctly

The screen will read Clone.



### Repeat

Repeat this on any other radio you wish to clone.



### Begin Cloning

Press the Push-To-Talk button on the master unit to begin the cloning process.



### While Cloning

The LED on the master radio will be steady red while the rest will blink red and green.

# JTECH<sup>®</sup> EXTEND Two-Way Radios

## Wireless Cloning



### Cloning is Complete

The master radio will return to the clone screen, the rest of the radio's screens will either say "ok" if the cloning process was successful or "error" if something went wrong.

*If "error" is displayed, repeat the cloning process for all radios that displayed "error."*



### To Resume Normal Usage

Turn all of the radios off and back on to resume normal usage after cloning is complete.



## Please Note

### Any Radio Can Become the Master

When the push-to-talk button is pressed on any radio it will become the master radio even if it is not the one you want to use. Be careful when cloning that only the master radio's push-to-talk button is pressed.